ÂÃí³ÛÝáõÃÛáõÝ ã³÷áÕ PH – 201

Operating Temperating	0°C to 50°C (32°F to 122°F)
Operating Humidity	Less than 80% RH.
Calibration Knob	External PH 4 (slope adj.) & PH 7 (Cal. adj.).
Power Supply	006P DC 9V battery.
Power Consuption	Approx. 2.0 mA.
Dimension	131 x 70 x 25 mm, (5.2 x 2.8 x 1.0 inch).
Weight	153 g/0.34 LB (including battery).
PH electrode (Optional)	Any connector PH Electrode with BNC connector.
Standard Accessories	Instruction Manual.....1 PC
Optional Accessories	PH electrode, Carrying case.

ÂÃí³ÛÝáõÃÛáõÝ ã³÷áÕ ë³ñù – å³ñ½¨Ñ³ë³ñ³Ï: ¾É»Ï ïñá¹Á ë³ñùÇÝ ÙÇ³óÝ»Éáõó ³é³çë³ñùÁ åÇïÇ³Ýç³ï í³ÍÉÇÝÇ: ê³ñùÇ×ßï·ñÇï ÉÇÝ»ÉÁ Ï³½ÙáõÙ¿ 0.1(ï³ëÝáñ¹³Ï³Ý): ØÇ³Ý³Éáõó Ñ»ïáã³÷Ù³Ý×ßï·ñÇï óáõóÙáõÝùÁë ï³óíáõÙ¿ 10 í³ñÏÛ³ÝÇó ÙÇÝç¨ 1 ñáå»: ºÃ» ã³÷íáõÙ¿ Ýáõ۝Ñ»ÕáõÏÁ Ï³Ù ÉáõÍáõÛÃÁ, ³å³ å»ïùã» ¿É»Ï ïñá¹Á ³Ù»Ýã³÷»ÉáõóÑ» ïáÉí³Ý³É (Ù³ùñ»É): æáõñÁ áõÕÕ³ÏÇ Íáñ³Éáí ÉóÝáõÙ »Ýù¿É»Ï ïñá¹Ç íñ³, ³ÛÝáõÑ» ï¨Ã»Ã¨Ã³÷ »Ýù ï³ÉÇë ¿É»Ï ïñá¹Á¨Ù³ùáõñ ³ÝÓ»éáóÇÏáí ëñ÷áõÙ¿É»Ï ïñá¹Ç ³ÛÝÙ³ëÁ, áñÁß÷í»É¿Ñ»ÕáõÏÇ Ñ»ï, µ³Ûóáã ÙÇ ¹»åùáõÙ ãÇ Ï³ñ»ÉÇ ¹Çåã»É·ÉËÇÏÇÝ: Þ³µ³ÃÁÙ»Ï ³Ý·³Ù ËáñÑáõñ¹¿ ïñíáõÙ¿É»Ï ïñá¹Á É í³Ý³É ëåÇñ ïáí Ýáõ۝ëÏ½µáõÝùáí: ¶ÉËÇÏÇÝ ¹Çåã»Éáõ ¹»åùáõÙ¿É»Ï ïñá¹Á ß³ñùÇó ¹áõñë¿ ·³ÉÇ: ´³Ûó³í³ñï»Éáõó ³Ýå³Ù³ÝÉí³ÉÃáñ³Í çñáí (»é³óñ³Í çáõñÁ – Ãáñ³Í çáõñ ã»): ¾É»Ï ïñá¹Á áã Ãáñ³Í çñáí Éí³Éáõ ¹»åùáõÙ ëË³É óáõóÙáõÝù¿ ï³ÉÇ¨ß³ñùÇó ¹áõñë·³Éáõ Ñ³í³Ý³Ï³ÝáõÃÛáõÝÁ Ù»Í³Ýáõ Ù¿: ¾É»Ï ïñá¹Á Ã»Ã¨³ÏÇ ß÷áõÙ (Ñ³ñáõÙ) »Ýù Ñ»ÕáõÏÇ Ù»ç, áñåÇë½Ç¿É»Ï ïñá¹Ç·ÉËÇÏÁ É³í ß÷íÇã³÷íáÕ Ñ»ÕáõÏÇ Ñ» ï: ¾É»Ï ïñá¹Á áã û·ï³·áñÍ»Éáõ Å³Ù³Ý³Ï å»ïù¿å³Ñ»É Çñ Ñ³Ù³ñÝ³Ë³ï»ëí³Í ÉáõÍáõÛÃÇ Ù»ç: ¾É»Ï ïñá¹Á µ³óíÇ×³ÏáõÙ å³Ñ»É ãÇ Ï³ñ»ÉÇ ³é Ñ³ë³ñ³Ï: 1 Å³Ù¨³í»ÉÇÝ µ³óÙÝ³Éáõ ¹»åùáõÙ¿É»Ï ïñá¹Á ß³ñùÇó ¹áõñë¿ ·³ÉÇ: ¾É»Ï ïñá¹Á ½»ñÓ å³Ñ»É Ñ³ñí³ÍÝ»ñÇó ¨ ÁÝÏÝ»Éáõó: â³ åáõÙÇ ×ßï·ñÇï ÉÇÝ»ÉÁ Ï³Ëí³Í¿ ã³÷íáÕ Ñ»ÕáõÏÇ ç»ñÙ³ëï Ç×³ÝÇó: ²Ûë Ñ³ë³ñ³Ï ëùÇ ã³÷Ù³Ý ¹»åùáõÙ ç»ñÙ³ëï Ç×³ÝÁ åÇïÇ ýÇÏëíÇ ï í³É µáÉáñ ã³÷íáÕ ³Ù³ÝÝ»ñáõÙ:

V A L **Automation** ***Tel :*** **00374-10-566720** ***Fax :*** **00374-10-543448** ***E-mail :*** **VAL@web.am**, ***URL :*** **www.val-automation.am** ***Address :*** **No17, Demirchian St. Yerevan 0002, Armenia**	**Simple Automation Systems** **Controllers** **PLCs** **Inverters** **AP Digital Instruments**
Sell → Consultation → Performance → Support → Service	
ì³×³éù, ÊáñÑñ¹³ï íáõÃÛáõÝ, è»³É½³óÇ³, ê å³ë³ñÏáõÙ	